


Tools Required:

For 24V LED luminaires

Dimensions**A:** 8"**B:** 6-1/4"**C:** 4-3/8"

Suitable for wet locations.

Notice to Installer for LED remote wiring:

1. DISCONNECT POWER BEFORE INSTALLATION AND/OR REMOVAL OF THE UNIT.
2. UL rated NEMA 3R rain tight steel box supplied with enclosed driver.
3. Install in accordance with national and local electric codes.
 - Input voltage: 120V-277V
 - Output DC: 24V
 - Max. output load: 25W
 - Min. supply wire: 18 AWG
 - Min. remote temp: -20° C

NOTE: The maximum wire distance before EMI (Electromagnetic Interference) can become a factor is 32 feet. For longer runs, to minimize EMI effects, the use of twisted shielded pair wires and Ferrite Coils at the beginning and end of the secondary line is suggested.

LED remote driver 19 580 - wiring instructions (see diagram):

1. Connect main voltage supply wire (line hot) to BLACK driver input wire
2. Connect neutral (common) supply wire to WHITE driver input wire
3. Connect red (positive) driver output wire to positive LED fixture wire(s).
4. Connect black (negative) driver output wire to negative LED fixture wire(s).

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.