

Tools Required:

- 3mm hex key
- 11/32" Nut driver
- Philips medium screwdriver
- Adjustable wrench



Dimensions

- A: 7-1/2"
- B: 6-1/8"



Protection Class: IP65

Weight: 5.1 lbs.

Notice to Installer for 66 978:

1. BEGA luminaires may be damaged if connected to conduit systems containing water- Article 300-5G of National Electric Code requires that "Conduits or raceways through which moisture may contact energized live parts shall be sealed or plugged at either or both ends".
2. Mounts directly to a standard octagonal 4" wiring box (by others) using mounting kit (supplied).
3. In conformance with U.L. Standards 1598, a silicone-based sealant MUST be used between the mounting plate edge and supporting wall.
4. LEDs are high-quality electronic components! Please avoid touching the light output opening of the LED directly during installation.

66 978 - installation:


1. Unscrew trim ring and lens from luminaire housing to disassemble.
2. Feed luminaire wires through fixture base, IP nipple (provided), and center hole in mounting strap.
3. Make supply wiring and luminaire wiring connections inside the octagonal wiring box:

MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE  
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE  
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE

Dimming (if applicable):

DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER DIM CONTROL WIRE  
DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER DIM CONTROL WIRE

4. Attach mounting strap (provided) to wiring box using outlet box screws (by others).
5. Attach 1/4" nipple to mounting strap and place luminaire over nipple.
6. Use lockwasher and nut (provided) to secure luminaire on nipple. Tighten nut.
8. Screw trim ring with lens onto luminaire housing, making sure the gasket is sealed properly.



Relamping/Maintenance

No relamping required.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

| Description            | Part No      |
|------------------------|--------------|
| Face Plate             | FP6978       |
| LED Driver (120V-277V) | 75987        |
| LED Module (3000K)     | LED-0310/930 |
| LED Module (4000K)     | LED-0310/940 |

Lamp: 15.7W LED

**Product Safety Warnings:**

**THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.**

**MIN 90°C SUPPLY CONDUCTORS.**

**CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.**

**LES FILS D'ALIMENTATION 90°C MIN.**

---